

ICE DOOR MOTOR



1. Unplug refrigerator or disconnect power.
2. Disconnect the motor connector at P5 on the core board.
3. Set the ohmmeter to the R x 1 scale.
4. Touch the ohmmeter test leads to the following motor connector pins:
Pin 1 to pin 2,3,5,or 6 = 45 to 55 Ω